# CP-A222WNM

# ULTIMATE 究極 SHORT THROW



The light weight and compact CP-A222WNM Ultimate Short Throw projector offers the highest quality images with a compelling design and low cost of ownership. With the bundled wall mount and optional table top kit you can project onto any existing whiteboard, wall or table top. Easy to install and flexible to use with optional wireless networking making the CP-A222WNM the ideal solution for any education or corporate environment.

### **Performance**

- XGA resolution (1024 x 768)
- 80" (2m) image from only 50cm\*
- 2200 ANSI Lumens (Bright Mode)
- Full connectivity including HDMI
- Perfect Fit adjust all four corners and sides of the image individually to achieve a square image
- Input Source Naming
- My Button
- Table top mount facility
- 10W speaker
- Anti theft features including:
  - PIN-Lock
  - MyScreen Lock
  - Transition Detector
  - Security bar

## **Cost of ownership**

- Extended Hybrid Filter life: 4000hr cleaning cycle
- Extended lamp life: 5000hrs (Normal Mode)
- Virtually maintenance free
- Easy set up and installation New on screen installation guide
- Power Saving Mode (ImageCare<sup>™</sup>)
- Wall mount included in the box

## **Advanced Network Features**

- Full connectivity including 1 x RJ-45
- Optional wireless networking<sup>†</sup>
- Configure and control projector via network with a web browser
- Projector management via SNMP
- Content via LAN
- AMX Device Discovery
- Messenger
- Cloning function
- PJ Link<sup>™</sup>
- Network Bridge
- iOS Connectivity

## **Environment**



- reduction in carbon footprint

  ImageCare™ The combination of Eco
- and Saver Modes conserve energy

Hitachi have formulated an "Environmental Vision" to contribute towards building a sustainable society through business and product development.

Our goal is to develop life-enhancing technology that will contribute to and realise a truly sustainable society for current and future generations.

\*From centre of mirror to screen. †Wireless is optional on this model (USB wireless adapter sold separately).















# CP-A222WNM

Technical Specifications








Table mount (optional)





Throw distance (from the top of the lens)						
Screen size	HxV		a1	a2	b1	b2
(diagonal)	(m)	(m)	(m)	(m)	(m)	(m)
60" (1.5m)	1.2	0.9	0.096	0.373	0.281	1.196
70" (1.8m)	1.4	1.1	0.161	0.437	0.317	1.384
80" (2.0m)	1.6	1.2	0.225	0.501	0.352	1.571
90" (2.3m)	1.8	1.4	0.289	0.566	0.387	1.759
100" (2.5m)	2.0	1.5	0.353	0.630	0.423	1.947













### OPTICAL

0.63" (1.6cm) P-Si TFT x3 I CD panel Resolution

2200 ANSI Lumens (Bright Mode)/1500 ANSI Lumens (Normal Mode) 2200 ANSI Lumens (Bright Mode)/1500 ANSI Lumens (Normal Mode) Light output (brightness) Colour light output (colour brightness)

Contrast ratio 4000:1

Free shaped lens and motorised free shaped mirror Lens Lamp Wattage

3000 Hours (Bright Mode)/5000 Hours (Normal Mode)\* Lamp life Focus distance 0.4m~0.7m (from mirror top to screen plane)

Distance to width ratio (:1) 0.3:1 (fixed) Diagonal display size 60~100" (152~254cm) Number of colours 8 Bit/colour, 16.7M colours

Fixed 6.1:-1 upward shift Normal at 71.1° projection angle Keystone

### COMPATIBILITY

Computer compatibility IBM Compatible VGA, SVGA, XGA, WXGA, WXGA+, SXGA,

SXGA+, UXGA (compressed), MAC 16" NTSC, PAL, SECAM, PAL-M, PAL-N, NTSC4.43 Composite/S-Video

Component Video

525i(480), 525p(480p), 625i(576), 1125i(1080i@50/60), 1125p(1080p@50/60), 750p(720p@50/60) 1125i(1080i@50/60), 750p(720p@50/60), 1125p(1080p@50/60) HDMI

Plug & Play DDC2B

Basic functions

10W x 1 Mono Speakers

Freeze, Magnifying, Blank, Auto adjustment, Mirror reverse image. Up-side down image. Auto signal search Digital Zoom x 1.35, Equalising Digital Gamma Correction,

Picture adjustments 2-3 pull down for NTSC, Progressive Scan, Noise reduction, Aspect selection 4:3/16:9/16:10/14:9/Native - dependant on source, Equalising colour temperature adjustment, Perfect Fit Horizontal  $\pm 5^{\circ}$ , Vertical  $\pm 5^{\circ}$ 

Digital keystone

Advanced features Drawing function (optional wireless tablet TB-1 required), My Screen, My Memory, My Button by remote control, My Source, My Text, Picture mode (8 modes), Source naming (English), Resolution setting, Template,

Saving mode, Audio pass through, Cloning, Audio sound mixing, Audio out (standby) and monitor out/selectable source with menu, Eco Mode (Normal, Eco, Intelligent Eco, Saver), Filter timer/selectable interval time, PC-less Presentation (JPEG, PNG, BMP, GIF, AVI, MOV), Stand-by Audio, On screen installation guide, iOS Connectivity

Easy Lamp replace from Top, Rear intake air filter Direct on, Auto off, Auto eco mode Outward

Power on & off PIN Security Lock, Myscreen Password Lock, Transition Detector, My Text Password Lock, Key Lock (key pad, remote control), Security systems

Kensington slot, Security bar, Lens door lock Configure and control projector via web browser, Failure and warning alerts via e-mail, Scheduling, My Image (still image transfer display), Network

Displaying text data transferred via the network, Command Control via network, Crestron RoomView® (not accessible through wireless adapter), AMX Device Discovery, Projector management via SNMP, PJ Link™, Network Bridge, Network Presentation (PC still picture transfer), MAC address on side, USB Display

33, including: English, French, German, Spanish, Italian, Norwegian, Dutch, Japanese, Portuguese, Swedish, Russian, Finnish, Polish, OSD languages options

Turkey, Arabic, Czech, Danish, Hungarian, Romanian, Slovenian, Croatian, Greek, Lithuanian, Estonian, Latvian

1 x HDMI (HDCP compatible) Digital input 2 x 15-pin Mini D-sub 1 x 15-pin Mini D-sub Computer input Monitor output

Video input 1 x RCA Jack (for composite), 1 x S-Video Jack

2 x Component D-sub (shared with analogue computer in 1/2) 2 x Stereo Mini Jack, 1 x pair RCA (L/R), 1 x Microphone Jack Audio input

Audio output 1 x pair RCA (L/R)

Control 1 x 9-pin D-sub for RS232 control LISR 2 x USB type A, 1 x USB type B

Wired network 1 x RJ-45 Wireless network Option, IEEE801.11b/g/n ready (optional wireless adapter required)

AC100-120V/220-240V, auto switching 300W (AC220-240V)/<0.35W Power supply Power consumption/standby

Weight

PHYSICAL

Dimensions (W x H x D) 345 x 85 x 303mm (excluding feet and extrusions when mirror is closed) 3.8Ka

34dB (Bright)/28dB (Normal) Noise level

Operating 0°C~40°C, Storage -20°C~60°C Ambient temperature Air filter

Hybrid

Lamp indicator light, power light, ceiling mount image, rear projection image, serial number label on side, Tabletop use (optional stand is required)

UL60950-1/ cUL, FCC Part15 subpart B class B, CE Marking: EN61000-3-2, EN61000-3-3 EN55022(class B), EN55024(EMC directive), EN60950-1 (Low voltage directive), WEEE/RoHS,/ErP(lot6) compliant, c-tick class B (Australia/New Zealand), GOST-R (Russia)

### ACCESSORIES SUPPLIED

Remote control with batteries, RGB cable, power cord, cable cover, security label, user manual (detail & concise), application CD, wall mount (HAS-K250), adapter cover

## OPTIONAL ACCESSORIES

Replacement lamp DT01381 Table top stand TT-251 Wireless pen tablet TR-1 Interactive camera unit IM-1 USB-WI -11N USB wireless adapter

Projector warranty 3 Years Lamp warranty 3 Years\*\*

HITACHI DIGITAL MEDIA, Hitachi Europe Ltd., Whitebrook Park, Lower Cookham Road, Maidenhead, Berkshire SL6 8YA UNITED KINGDOM

Tel: +44 (0)1628 585 000 Fax: +44 (0)1628 585 163 www.hitachidigitalmedia.com

"The stated lamp and filter (life refers to the average life expected in ideal operating conditions with usage in accordance with the manual. The majority of, but not all lamps and filter should achieve this figure. "Where a lamp falls within warranty and a replacement lamp is taken, the warranty for the replacement lamp will be a maximum of 3 years (dependent on warranty hours stated). HDMI, the HDMI logo and High-Definition Multimedia Interface are trademarks or registered trademarks of HDMI Licensing LLC. AMX and the AMX logo, and Device Discovery are all registered trademarks of AMX. The specification above and photography is for reference only and may be subject to change.